Ailunce HA1G Firmware upgrade operation

Download APP application:

https://www.ailunce.com/Supports/HA1G/Software

1. Open upgrade tool.

HA1G host u	ipgrade tool		1000		Х	
App bin file	0240727\2、固件升级文件\H	HA1G_app_V1.01.10.005_20240727\HA1G_app	_V1.01.10.005_20	0.005_20240727.		
		port: COM9 🗸	U	p <mark>d</mark> ate(<u>U</u>	<u>l)</u>	
					^	
					>	
<				>		

2. Choose the correct com port. The HA1G USB driver should be named

as " USB-SERIAL CH340".

✓ 員 端口 (COM 和 LPT) 員 USB-SERIAL CH340 (COM9)

3. Click "Update".

App bin file	t upgrade tool 0240727\2、固件升级文件\HA1G_app_V1.01.10.005_20240727\HA1G_app_V1.01	.10.005_		× 7.bir
	port: COM9 ~	[Update	(<u>U</u>)
				^
	Waiting for the host to enter upgrade mode 299/300			
	Cancel(C)			

4. Radio enter the DFU mode.

Press PTT+SK1 together, and then turn on the radio.

5. It is going to upgrading progress.

	10/2/ /2 / EIT/13% / I / //// EBP / 1/01/10/000_202/07 / ///// EBP _	1.01.10.000_20210727.01
	port: COM9 🗸	Update(U)
16 16 16 16 16 16 16 16 16 16 16 16 16 1	writing data 8%	

6.	After	update	successfully,	the radio	will turn	on automatical	ly.
----	-------	--------	---------------	-----------	-----------	----------------	-----

pp bin file	0240727\2、固件升级文件\HA1G_app_V1.01.10.005_20240727\HA1G_app_V1.01	.10.005_	20240727	.b
	port: COM9 ~	[Update(<u>U)</u>
A 75 6D 70 6 20 53 69 6 43 5 6 6 6 6 6 6 6 6 6 6 6 6 6 6 6 6 6 6	0 20 74 6F 20 41 70 70 20 28 27 34 27 29 2E 2E 20 0D 0A F8 7A 65 20 3D 20 34 39 32 35 34 34 20 2D 20 34 39 32 33 36 34 0D 0A 44 6F 77 6E HA1GUpdateTool X The host writes successfully 确定	E 6C 6F 6	1 64 20 4	3
)6)4				